



Electrical and Computer Engineering Department
 University of Maryland
 College Park, MD 20742-3285

Glenn L. Martin Institute of Technology ♦ A. James Clark School of Engineering

Dr. Charles B. Silio, Jr.
 Telephone 301-405-3668
 Fax 301-314-9281
 silio@umd.edu

ENEE 350 Homework Set 7

Programming Project 2

(Due: Class 17, Mon., Mar. 30, 2015)

Write, assemble and run successfully on the simulator a Mac-1 subroutine **lgneg(n,x)** that returns in the AC the address of the integer possessing the algebraically largest negative value along the real line among the n integers in the array whose starting address is x. The largest negative value on the real line is the farthest right value to the left of (i.e., closest to) zero. If there are no negative values among the n elements to be processed, then return -1 which is equivalent to the (unsigned) address 65535, or if we strip off the high order 4 bits, it corresponds to address 4095, the output status register; clearly, neither is a valid memory address for an array element. If there are two or more array entries that equally satisfy the requirements, return the address of the one with the highest (greatest) address. Your subroutine should be tested with the main program shown below, which defines how the parameters are passed.

/main program				/continued from below halt	
	EXTRN	lgneg		data	57
ans1	RES	1			0
ans2	RES	1			129
ans3	RES	1			34
n1		6			8
n2		10			3
n3		5			-29
start	loco	4020			-15
	swap	/initialize sp			-2
	loco	n1			-347
	push	/push address n1			-3
	loco	data			6
	push	/push array start address			35
one	call	lgneg			-413
	stod	ans1		END	start
	insp	2			
	loco	n2 /push address n2			
	push				
	loco	data			
	add	(4)			
	push	/push array start address			
two	call	lgneg			
	stod	ans2			
	insp	2			
	loco	n3 /push address n3			
	push				
	loco	data			
	add	(9)			
	push	/push array start address			
three	call	lgneg			
	stod	ans3			
	insp	2			
	halt				
	/data array continues here but				
	/ is shown in the above right hand column				

Hand in a copy of the main program symbolic assembly listing, the subroutine symbolic assembly listing, the contents of (macro) memory after "load main sub" (i.e., of main.abs) before execution of the program, and the contents of memory after execution of the program. Highlight and comment upon the final answers. Specify what values are contained in the addresses specified by ans1, ans2, and ans3.