



ENEE 350 Homework Set No. 6

(Due: Class 15, Wed., June 25, 2014)

1. Read textbook section 5.4. (Also, reread sections 5.5 and 5.6, especially 5.5.7.)
2. Work text problem 5-6.
3. Work text problem 5-25.
4. Print out and read the notes on PDP-11 addressing on the course webpage under the subdirectory Notes. Then work the following problems:

- a. Suppose a DEC PDP-11 instruction word fetched and placed in the IR contains the bit pattern:
 0001100100010001

Just before this instruction is executed, relevant registers and memory locations contain the following:

| | |
|----------------------------|---|
| [R1] = 002000 ₈ | [2000] ₈ = 002002 ₈ |
| [R2] = 002002 ₈ | [2002] ₈ = 002004 ₈ |
| [R3] = 002004 ₈ | [2004] ₈ = 002006 ₈ |
| [R4] = 002006 ₈ | [2006] ₈ = 002010 ₈ |
| [R5] = 002010 ₈ | [2010] ₈ = 002012 ₈ |
| | [2012] ₈ = 002000 ₈ |

Give the (octal) contents, immediately after execution of the instruction in the IR, of registers and any memory locations whose contents could have changed by execution of this instruction.

- b. Suppose instead that the PDP-11 instruction fetched into the IR is given by the bit pattern:
 0110100100010001

and suppose the contents of registers and memory locations are the same as is given in part a. Now what are the octal contents of registers and memory locations changed by execution of this instruction?

5. Another PDP-11 problem: Suppose the IR contains the following bit pattern:
 0001001001001010

and suppose that registers and memory locations contain the following:

| | |
|----------------------------|---|
| [R0] = 001000 ₈ | [1000] ₈ = 001000 ₈ |
| [R1] = 002000 ₈ | [2000] ₈ = 004000 ₈ |
| [R2] = 003000 ₈ | [3000] ₈ = 005000 ₈ |
| [R3] = 004000 ₈ | [4000] ₈ = 002000 ₈ |
| [R4] = 005000 ₈ | [5000] ₈ = 000000 ₈ |

Give the (octal) contents, immediately after execution of the instruction in the IR, of registers and any memory locations whose contents could have changed by execution of this instruction.

6. The DEC PDP-11 instruction word in memory location i is fetched and placed in the IR for decoding and execution; this word contains the bit pattern (shown in binary); also shown is the word that follows it in memory:

$$\begin{aligned} 1110100001110011 &= [ir] = m[\text{word } i] \\ 0000000000000110 &= m[\text{word } i+2] \end{aligned}$$

Just before this instruction is executed, relevant registers and memory locations contain the following (in octal shorthand):

| | |
|----------------------------|---|
| [R0] = 002014 ₈ | [2000] ₈ = 002002 ₈ |
| [R1] = 002002 ₈ | [2002] ₈ = 002004 ₈ |
| [R2] = 002004 ₈ | [2004] ₈ = 002006 ₈ |
| [R3] = 002006 ₈ | [2006] ₈ = 002010 ₈ |
| [R4] = 002010 ₈ | [2010] ₈ = 002012 ₈ |
| [R5] = 002012 ₈ | [2012] ₈ = 002000 ₈ |
| [R6] = 002000 ₈ | [2014] ₈ = 164163 ₈ |
| [R7] = 002016 ₈ | [2016] ₈ = 000006 ₈ |

Give the (octal) contents, immediately after execution of the above instruction and immediately before start of the fetch cycle for the next instruction, of only those registers and memory locations whose contents have been changed during execution of this instruction.

7. Read Chapter 7 in A. S. Tannenbaum, *Structured Computer Organization*, 5th. ed., Prentice Hall, 2006, and learn how assemblers and linkers work.
8. Programming Assignment 1: Consider the following main program and subroutine for the MAC-1 machine:

```

                /Main
                EXTRN  sum
ans1            RES    2
ans2            RES    1
start          loco   4020
                swap
                stod   ans1
                loco   x1
                push
                lodd   x2
                push
                loco   ans1
                push
                call   sum
                stod   ans2
                halt
x1              -40
x2              19
                END    start

                /Subroutine sum
                ENTRY  sum
i               EQU    1
j               EQU    2
k               EQU    3
sum            lodl   j
                addl   k
                push
                lodl   j
                addd   (1)
                popi
                lodl   k
                pshi
                pop
                addd   (-23)
                retn
                END
    
```

Add comments to each line of code in the main program and subroutine explaining what is taking place (and preferably why); don't simply restate the obvious. Adjust the comments after you analyze the programs (using the simulator) so that they meaningfully describe the code.

Assemble, link, and simulate execution of the above main program and subroutine. Do two different simulations. Turn in printouts of the separate assemblies, linkages, and the snapshots of memory before and after execution in each case. Write up a summary of the differences in the addresses used in the two different absolute programs, and place comments on the symbolic source statements to describe what the program statements are accomplishing. Explain the final contents of locations ans1, ans1+1, and ans2.

Assuming that the main program is in file "main" and that the subroutine is in the file "sum", be sure to do the following:

```

assem main
qpr -q "your favorite printer" main.list
assem sum
qpr -q "your favorite printer" sum.list
load main sum
qpr -q "your favorite printer" main.abs
sim main.abs $EE350/halt $EE350/halt.pascal
    
```

- produce printout of before and after memory contents and highlight and explain the contents of ans1, ans1+1, and ans2.

```

Also, do the following: load sum main
qpr -q "your favorite printer" sum.abs
sim sum.abs $EE350/halt $EE350/halt.pascal
    
```

- produce printout of before and after memory contents and highlight and explain the contents of ans1, ans1+1, and ans2.

Note: Be sure to edit the memory dumps to get rid of excess words with all zeros (however, be sure to keep both the code and stack sections of memory from both sets of dumps). Both sets of dumps should fit on one page with judicious editing and use of `enscript`.